



TECHNICAL BULLETIN: BATMAN

SN: 1000- 1204

IMPORTANCE: URGENT

DATE: 11/27/13

SUBJECT: BATMAN

PROBLEM: NOT LINKING

SOLUTION: ENABLE INTEGRATED NIC SETTING IN BIOS (DELL OPTI 3010)

PROCEDURE: CHANGE BIOS SETTING: ENABLE NIC

1. TURN OFF POWER TO THE GAME
2. REMOVE BOTTOM BACK DOOR TO ACCESS PC
3. CONNECT A USB KEYBOARD TO THE PC USING ANY AVAILABLE USB SLOT
4. TURN THE GAME 'ON' WHILE HOLDING DOWN THE F2 KEY
5. FOLLOW THE PROCEDURE ON PAGE 2 OF THIS DOCUMENT ON HOW TO CHANGE THE BIOS SETTINGS.
6. SET INTEGRATED NIC: ENABLED.
7. SAVE NEW SETTING AND EXIT BIOS
8. PC WILL RESET AND LOAD THE GAME

ENABLE MULTIPLAYER LINK ON BOTH UNITS!

9. ENTER THE TEST MENU BY PRESSING THE 'TEST' BUTTON ONCE GAME IS LOADED.
10. FROM THE MAIN MENU → ADJUSTMENTS → MULTIPLAYER ADJUSTMENTS
11. SET GAME "MULTIPLAYER LINK" : ENABLED
12. EXIT THE TEST MENU
13. VERIFY THAT LINK IS SUCCESSFUL BY STARTING A LINKED GAME.

END OF PROCEDURE.

NOTE: For technical assistance please call Betson at 800-753-2513

BIOS Settings/Power Management

NOTICE

The PC ships with correct BIOS settings. Making changes to the BIOS different from the description below may adversely affect game functions. Do **not** use the PC on/off switch. Turn AC power on or off with the cabinet power switch.

1. Turn cabinet power switch off.
2. Open rear of cabinet.
3. Connect a USB keyboard to the PC.
4. While holding the F10 key on the keyboard down, turn cabinet power switch on.
5. When the BIOS menu screen appears, make the following adjustments shown below. Note: Most settings use the default.
6. Follow instructions on screen to save and exit.
7. PC will reset and load the game.

```
8. -General
9.     +System Information => n/a
10.    +Date/Time => n/a
11.    +Boot Sequence :
12.        -[1]CD/DVD/CD-RW Drive
13.            -[2]Onboard SATA
14.            -[disabled] USB Storage Device
15.            -[disabled] Diskette Drive
16.            -[disabled] Onboard NIC
17. -System Configuration
18.     +Integrated NIC : Enabled           <<<<<<<<<<<< SET TO "ENABLE">>>>>>>>
19.     +Serial Port: DISABLED
20.     +SATA Operation: ATA
21.     +Drives: all enabled (all checked)
22.     +SMART Reporting: disabled (not checked)
23.     +USB Configuration: all enabled (all checked)
24.     +Miscellaneous Devices : n/a
25. -Video
26.     +Multi Display : Disabled
27. -Security: no changes
28. -Performance
29.     +Multi Core Support : All
30.     +Intel Speedstep : Disabled
31.     +C States : Enabled
32. -Power Management
33.     +AC Recovery : Power ON
34.     +Auto ON Time : Disabled
35.     +Deep Sleep Control : Disabled
36.     +Fan Control Override : Disabled
37.     +Wake on LAN : Disabled
38. -Post Behavior
39.     +Numlock LED : Enabled
40.     +Keyboard Errors : Disabled
41.     +Post Hot Keys : Enabled
42.     +Fastboot : Thorough
43. -Virtualization Support
44.     +Virtualization : Enabled
45.     +VT for Direction I/O : Disabled
46. -Maintenance => n/a
47. -ImageServer => n/a
48. -System logs => n/a
```